


Bedienungsanleitung

Instruction Manual



Lieferumfang

Scope of delivery

1x LED Wandeinbauleuchte
1x Bedienungsanleitung

1x LED recessed wall light
1x Instruction manual

Bedienungsanleitung für MATO LED Wandeinbauleuchte WL-014

Lesen Sie bitte alle Anweisungen und Hinweise sorgfältig durch. Bewahren Sie im Anschluss diese Anleitung gut auf, um später bei Bedarf darin nachschlagen zu können. Wenn Sie das Produkt an jemand anderen weitergeben, geben Sie auch diese Anleitung mit. Diese LED-Wandeinbauleuchte ist ausschließlich für den Privatgebrauch bestimmt und nicht für den gewerblichen Bereich geeignet.

Please read all instructions and notes carefully. Keep these instructions in a safe place for future reference. If you pass the product on to someone else, please also include these instructions. This LED recessed wall light is intended for private use only and is not suitable for commercial applications.

Hinweis

Note

Abdeckungen sind in verschiedenen Ausführungen optional erhältlich und können separat bestellt werden.

Covers are available in various designs as an option and can be ordered separately.

Technische Daten

Technical Data

Modell	WL-014
Eingangsspannung	220-240V 50/60Hz
Leistung	0,5W – 2,5W einstellbar
Lichtfarbe	3000K Warmweiß / 4000K Neutralweiß (einstellbar)
Arbeitstemperatur	5°C – + 45°C
Schutzart	IP44 (Indoor)
Schutzklasse	SK II
Material	Aluminium, Polycarbonat
Produktabmessung	Ø 75 X 40 mm

Model	WL-014
Input voltage	220-240V 50/60Hz
Power	0.5W – 2.5W Adjustable
Light temperature	3000K warm white / 4000K neutral white (adjustable)
Working temperature	5°C – + 45°C
Protection type	IP44 (Indoor)
Protection class	Class II
Material	Aluminium, Polycarbonate
Product dimension	Ø 75 X 40 mm

WICHTIG für den Gebrauch

IMPORTANT for use



- Die Installation sollte von einem qualifizierten Elektriker durchgeführt werden.
- Vor der Installation den Strom abschalten.
- Der Hersteller oder Händler übernimmt keine Haftung für Schäden die durch falschen Gebrauch entstanden sind

Sollten die vorgenannten Punkte nicht eingehalten werden, kann es zu einem Kurzschluss oder elektrischen Schlag kommen.

Es besteht Lebensgefahr!

- Installation should be carried out by a qualified electrician.
- Turn off the power before installation.
- The manufacturer or retailer accepts no liability for damage caused by improper use.




Failure to observe the above points may result in a short circuit or electric shock. **There is danger to life!**

Entsorgung

Disposal

Elektro Altgeräte bitte bei einer dafür vorgesehenen Sammelstelle entsorgen gemäß § 18 Absatz 4 ElektroG für private Haushalte.

Please dispose of old electrical devices at a designated collection point in accordance with Section 18 Paragraph 4 ElektroG for private households.



Montageanleitung

A. Strom abschalten

bevor Beginn der Arbeiten schalten Sie bitte die Stromzufuhr ab, um Ihre Sicherheit zu gewährleisten.

B. Montagearbeiten beginnen

1. Einbaudose vorbereiten und Elektrischen Anschluss herstellen

- Die Leuchte wird in eine standardisierte Unterputz- oder Einbaudose eingesetzt.
- Stellen Sie sicher, dass die Einbaudose fest montiert, sauber und trocken ist.
- Verbinden Sie die Anschlussleiter gemäß Klemmenbezeichnung (L / N).

2. Leuchte einsetzen und fixieren

- Setzen Sie die Leuchte gerade in die Einbaudose.
- Befestigen Sie die Leuchte mit den beigelegten Schrauben oder mit den für die Unterputzdose vorgesehenen Schrauben (Dosen-Schrauben).

3. Abdeckung aufsetzen

- Die Abdeckung wird magnetisch gehalten – einfach aufsetzen

4. Feinadjustierung

- Nachdem die Abdeckung magnetisch aufgesetzt wurde, richten Sie sie sanft nach, bis sie gleichmäßig und optisch sauber sitzt.

C. Strom einschalten und Funktionstest durchführen

Gut gemacht, viel Spaß mit der neuen Beleuchtung.

Assembly Instruction

A. Turn off power

Before starting work, please turn off the power supply to ensure your safety.

B. Start assembly

1. Prepare the mounting box and make the electrical connection

- The light fixture is installed in a standard flush-mounted or recessed junction box.
- Ensure the junction box is securely mounted, clean, and dry.
- Connect the wires according to the terminal markings (L / N).

2. Insert and secure the light fixture

- Insert the light fixture straight into the recessed mounting box.
- Secure the light fixture using the included screws or the screws designed for recessed mounting boxes (box screws).

3. Put on the cover

- The cover is held in place magnetically – simply place it on.

4. Fine adjustment

- After the cover has been magnetically attached, gently adjust it until it sits evenly and looks clean.

C. Turn on the power and perform a function test.

Well done, have fun with the new lighting.

Kompatibel mit
Compatible with



WL-014
CVR-01



WL-014
CVR-02



WL-014
CVR-05



WL-014
CVR-06

Scannen für

Video-Tutorial



or visit us :

www.mato-lighting.com/manuals

Sie haben Fragen? Wir sind für Sie da!
service@mato-lighting.com

MATOLUX GmbH

Johannes-Messner-Weg 1/5
6130 Schwaz
AUSTRIA



MADE IN PRC